

IRIS INSTRUMENTS

INDUCED POLARISATION TRANSMITTER



- Ease of use
- Robustness

- 2 400 V output voltage
- Standard motor generator

TIPIX MAJOR BENEFITS

- TIPIX is a **3 kW transmitter** designed for IP surveys and for deep resistivity soundings.
- It is microprocessor controlled for **ease of operation** and protection against misuse.
- A four line alphanumeric display is provided for the simultaneous indication of **all output parameters**: output current, output voltage, contact resistance and output power are continuously displayed
- A **standard motor generator** can be used to power the TIPIX

TIPIX MAIN FEATURES

- The TIPIX will generate up to **2 400 volts** for work in high resistivity areas and up to **13 amperes** for low resistivity regions.
- The TIPIX is designed for **ease of operation**. Four buttons on the front panel are used to select the desired options and to increase or decrease the current.
- **Limit values of voltage, current or power** can be introduced.
- **Messages and warnings** are displayed in case of problem or malfunction, for an easier identification of a trouble and a quicker instrument servicing.

TIPIX

RESISTIVITY & INDUCED POLARISATION 3 kW POWER TRANSMITTER

TIPIX TECHNICAL SPECIFICATIONS

- Output Power: 3 000 W maximum
- Output Voltage: 2 400 V maximum
- Output Current: 13 amperes maximum

TIME DOMAIN MODE:

- Waveform: ON+, OFF, ON-, OFF, (ON = OFF) preprogrammed cycle.
- Automatic circuit opening in OFF time.
- Preprogrammed ON times from 0.5, 1, 2, 4, and 8 seconds ON pulse duration.
- Display: Four line alphanumeric liquid crystal display.
- Simultaneous display of output current, output voltage, contact resistance, and input power
- Protection:
 - short circuit at 20 ohms,
 - open loop at 100 000 ohms,
 - thermal,
 - input overvoltage
 - input undervoltage.
- Possibility of gps synchronisation.

GENERAL FEATURES:

- Dimensions (h w d): 41 x 32 x 24 cm.
- Weight: 31 kg
- Power Source: 90 to 260 VAC, 45-450 Hz single phase
- Operating temperature: -30 to +50 °C.

